



## Wi-Fi Options and Settings

Your MyReadySpot is set up and working and you want to add additional WiFi profiles into it such as your cell phone as an internet source.

You are going to be traveling and you want to add additional profiles to your MyReadySpot.

You changed your WiFi SSID or WiFi password and now your MyReadySpot won't connect.

### To use the pistar recovery AP feature.

#### Step 1

Boot up your MyReadySpot and let it run for at least 2 mins.

#### Step 2

Using your control device, laptop, pc, iPad, tablet etc. Scan for WiFi access points you should see pistar as a WiFi source; Connect to it.

Password is raspberry

#### Step 3

When the control device has connected, open a web browser enter pi-star.local in the address bar, not the search bar. (\*see note)

#### Step 4

You will see the pistar dashboard. Click on configuration and you will be prompted to login.

Username: pi-star

Password: raspberry

#### Step 5

Navigate to WiFi set up (Configure WiFi) and search for networks or just add them in if you know the SSID and credentials. Your MyReadySpot will hold five or more network credentials.

## **Step 6**

Save changes and reboot. The MyReadySpot will cycle through the saved networks until it finds a working one and connect. Be sure to move your control device onto the same network as the MyReadySpot if you need to login to it.

### **Notes:**

\*If for some reason pi-star.local doesn't bring up the dashboard. Key your radio and the MyReadySpot will display your IP address on the screen of the MyReadySpot. Simply type that in and it should bring up your dashboard.